

Universal DSL Link Interface Between  
A DSL Digital Controller And A DSL Codec

FIELD OF THE INVENTION

The invention relates generally to a digital subscriber line (DSL)-link interface and protocol for a DSL modem. The present invention has particular applicability to personal computer (PC) systems where the digital control and analog front end portions of such a DSL modem are not implemented in a single integrated circuit (IC) for various technical and cost-effective reasons.

BACKGROUND OF THE INVENTION

It has been consistent in the electronics industry that complex logic functions are integrated into smaller and smaller form factors. For instance, a popular growing trend is to combine audio and telephone capabilities in one device, including graphic and video functions in a computer chipset, and to integrate all computer peripheral functions into a single IO chip. A related general trend in the PC industry is the migration of more and more devices, components, functionality, etc. to the motherboard. This makes sense for a variety of engineering and cost reasons, including the fact that this approach conserves available conventional expansion slots on the system bus, is easier to configure, reduces the total mother board form factor and BOM cost, and preserves compatibility with legacy systems.

At the same time, there are certain components that are not optimally combined or tightly integrated together for a variety of reasons, some of which are engineering related, and some of which are regulatory related. As noted above, there is considerable interest in placing a full scale modem down (directly on) the motherboard, to obtain the aforementioned benefits. From an engineering perspective, however, it is difficult to place the analog I/O portions of a modem directly on a motherboard because of various noise sources present on the latter. Therefore, the signal to noise ratio (SNR) performance of the modem system will decrease. Similarly, from a regulatory perspective, these analog portions of a modem must undergo a certification process in accordance with local applicable telecom rules and regulations before they can be implemented in a commercial

product. If it were necessary to subject every motherboard to a new certification process (simply because it now incorporated some modem front end circuitry), this would impede and slow down the development of new products considerably.

Thus, there is a general perception in the industry at this time that, at least for the  
5 PC environment, it makes more sense to separate the analog and digital portions of a high speed modem. This has led to a proposal, authored by Intel Corporation, known as the Audio/Modem Riser Specification, in which it is suggested that the analog I/O portions of a modem be moved to a card that is physically separated but easily connected to a motherboard. Version 1.1 of this document, revised on September 10, 1998, is available  
10 for downloading via the Internet at Intel's corporate web site, and is hereby incorporated by reference. In this specification, a portion of which is reproduced in FIG. 1A, it is proposed that the portions of the modem which are susceptible to noise, and which implicate certification issues, be moved to what is known as a Homologated Riser Card. This card has I/O connections to the outside world (i.e., such as to a conventional  
15 telephone line) but at the same time fits in a riser connector directly to the motherboard. As the specification indicates, this riser interface is preferably standardized, so the motherboard makers can implement audio/modem capability with lower BOM costs, and with fewer concerns about vendor proprietary variations (i.e., because there is a common footprint that can be stuffed with competing pin compatible implementations). The  
20 specification provides a detailed and comprehensive explanation of the electrical and physical requirements required to comply with the proposed standard.

As depicted in FIG. 1A, a modem 100 includes an analog I/O portion 110 located on a riser card 111. This analog I/O portion (sometimes referred to as a codec) is then interfaced through a digital link 120 (known as AC-97) to the digital controller 130 of the  
25 modem. The latter digital portion is located directly on a motherboard 131 and generally includes appropriate modem control circuitry, data pumps, and other functional circuits typically associated with those aspects of a modem. These functions can also be performed, for example, by a so-called host signal processing (HSP) embodiment, in which case the AC 97 digital controller (at least for the modem portions anyway) can

consist of as little as a very simple bus interface. The preferred implementation for this digital portion is described in another specification published by Intel known as Audio Codec 97. Version 2.1 of this document, published on May 22, 1998, is likewise available for downloading at Intel's corporate web site, and is also hereby incorporated by  
5 reference. As noted therein, the AC97 digital controller can include a wide range of capabilities, including multiple digital audio channels, and suitable interfaces to a PCI bus, a digital I<sup>2</sup>S bus, etc.

A description of the various I/O, control, and power/ground signals in the AC-97 link passing through the riser interface is provided at Tables 1 - 5 of the aforementioned  
10 A/M Riser specification. As seen generally in FIG. 1B, in a voice band modem implementation, the AC 97 link between the digital controller 130 and the analog CODEC 110 consists of a five wire, bi-directional, serial TDM format interface. The signals supported, include the following: RESET (a master hardware reset), BITCLK (12.288 MHz serial data clock), SYNC (48KHz fixed rate sample sync), SDATA\_OUT  
15 (serial, time division multiplexed input data stream to the PC), and SDATA\_IN (serial, time division multiplexed output data stream from the PC). The format and nature of these signals is well-known, and is described in the aforementioned specifications. Digital controller 130 can also including suitable interfaces for other contemporary expansion busses, such as PCI bus 141, USB 142, etc.

20 While the A/M Riser specification is a step in the right direction, it does not provide for functionality that would permit implementation of an xDSL type modem at this time. For example, xDSL requires a much higher bit rate than that provided by the AC97 link (at a 2.2 MHz sampling and 16 bits wide for an ADSL downstream signal, the total bit rate is 35.2 Mb/s, which is much higher than the 12.288 MHz serial clock).  
25 Furthermore, there are various power and control signaling requirements in xDSL that were not foreseen by AC97. Therefore, the AC97 and A/M Riser specification are limited to supporting at most simple analog type (V.90 and the like) modems. This is a significant drawback, since xDSL technologies (and especially ADSL) are expected to be in widespread use in a very short time.

SUMMARY OF THE INVENTION

Accordingly, it is a general object of the present invention to overcome the aforementioned problems.

Another object of the present invention, is to provide a DSL modem which is  
5 configurable as a motherboard device within a personal computing system, in a manner similar to that only currently possible for voice band type modems;

A related object of the present invention is to provide a DSL modem that has analog codec circuitry and digital controller circuitry both tightly coupled to a PC motherboard, in a manner similar to that only current provided for voice band type  
10 modems;

Another object of the present invention is to provide a DSL interface that can properly handle DSL data rates, DSL control signals, and other xDSL related signal requirements so that it is suitable for linking the analog and digital portions of a DSL modem of the aforementioned type;

A related object of the present invention is to provide a DSL interface that is  
15 extremely flexible, and can be used in any one of a number of different xDSL technologies, including HDSL, SDSL, ADSL, reduced rate ADSL, etc.;

Another object of the present invention is to provide an improved signal protocol for a DSL link, having data/control word formatting and timing specifications especially  
20 suited for a DSL data stream;

A further object of the present invention is to provide a DSL interface that minimizes the required signal and power pins associated with a standardized specification for analog codec components in a personal computing system, and is therefore cost effective, and can be easily integrated by system vendors;

Yet a further object of the present invention, is to provide a DSL digital controller  
25 and a DSL codec which can utilize the above novel DSL interface;

An additional object of the present invention, is to provide a personal computer motherboard which is adapted to use the aforementioned DSL modem and DSL interface.

Another object of the present invention is to minimize the required logic complexity in order to support all above functions and features.

These and other objects are effectuated by the following aspects of the present invention.

5 An improved digital communications link of the present invention connects a digital controller section of an xDSL modem - which is preferably located on a system motherboard of a computing system - to a separate analog section of the xDSL modem - which is located at a position substantially free of electronic noise from other electronic components on said motherboard, which could materially affect the operation of such  
10 analog section. The data path/link is generally configured in the following manner: (a) a plurality of receive signal lines are set up for receiving data from a remote site; (b) a plurality of transmit signal lines are designated for receiving data from a remote site; (c) a bit clock signal line is set up for carrying a clock signal, which clock signal is used in connection with communicating the data to and from the remote site. The bit clock signal  
15 line can carry any desired clock signal needed according to data transmission requirements of said digital communications link, thus providing a scalable interface that is easily adaptable for use in any number of different motherboard environments.

An additional word clock signal, derived from the bit clock signal, marks the boundary for each sample word received or transmitted on said plurality of receive signal  
20 lines and/or plurality of transmit signal lines respectively.

Another aspect of the present invention includes the use of an improved protocol for exchanging operational and/or control information between separated digital and analog sections of an xDSL modem. This operational and/or control information preferably includes information relating to real time control settings for circuits located  
25 within the analog codec, power management, and the like.

During normal operation, the aforementioned receive and/or transmit signal lines can also be used for carrying control words for use by the xDSL modem, which control words are embedded as part of the normal data stream. As a compromise between flexibility and speed, these control words preferably have either a first or second length.

The control word has a start bit, followed by a length indicator bit, and then the set of command bits corresponding to the actual command/data value. Idle bits are transmitted continuously between control words. Unlike prior art schemes, the control words are transmitted asynchronously, therefore, in an embedded operations channel (EOC) that has  
5 an effective rate equal to the word clock signal.

According to another useful feature of the present invention, the aforementioned link also includes provision for setting up a multi-channel data frame. In this way, two or more data channels can be set up between the digital controller and analog section, with data transferred through a first channel during a first time period of the multi-channel data  
10 frame, and through a second channel during a second time period of the multi-channel data frame. To accomplish this, the word clock signal can be adapted to have a different duration for different number of data channels. In one variation, the data channels can have different transmit and/or receive data rates, so as to accommodate multiple codecs, or unequal receive/transmit data stream bit rates (such as ADSL). Accordingly, the single  
15 channel limitation of the prior art can be also be overcome by this capability of the present invention.

Yet another useful aspect of the present invention provides that, due to the unique selection of receive/transmit/clock lines and signal protocols, the same receive and/or transmit signal lines can also be used to support a compatible data interface between the  
20 digital controller and an ATM based hardware xDSL modem. In other words, the data path can handle ATM packaged data and clocking information, making it extremely versatile and useful for incorporation within a motherboard application.

These aspects of the present invention thus permit an xDSL motherboard, and an xDSL modem to be configured in a manner similar to a voice-band modem.

25 A computer motherboard, DSL digital controller, DSL codec, and DSL modem of the present invention include otherwise conventional hardware (and/or software in an HSP application) and are all implemented with appropriate interface circuitry and control logic necessary to effectuate the above architecture, characteristics and functionality of the aforementioned DSL link.

Although the inventions are described below in a preferred embodiment associated with a personal computing system, it will be apparent to those skilled in the art the present invention would be beneficially used in any environment where it is desirable to link separated analog/digital portions of an xDSL modem.

5

#### BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1A is a diagram illustrating how an analog portion of a prior art voice band grade modem is mechanically placed in a riser card and electrically connected to a digital portion of such modem integrated into a computer motherboard in a personal computing system

10

Figure 1B is an electrical block diagram depicting the various signals carried by a prior art digital link for a voice band grade modem integrated as part of a motherboard in a personal computer system;

15

Figure 2A is a functional block diagram of a preferred embodiment of a DSL digital link, DSL modem, and motherboard of the present invention;

Figure 2B is a more detailed functional block diagram of the portions of the circuitry illustrated in FIG. 2A;

20

Figures 3A - 3C are preferred embodiments of timing specifications, data formatting, and control signal protocols used in the DSL link of the present invention;

Figure 4 is a preferred embodiment of a signal and timing protocol that can be used by the DSL link of the present invention to support an ATM interface.

#### DETAILED DESCRIPTION OF THE INVENTION

25

##### *DSL Modem System Overview*

A preferred embodiment of the present invention is depicted generally in FIGs. 2A and 2B. This embodiment is similar in some respects to the prior art voice band modem implementation shown in FIG.1, and, for that reason, like components/circuits are designated with like numerals. In FIG. 2A, an xDSL modem 200 as shown consists of

two physically separated (but electrically coupled) circuitry sections, a DSL Modem Analog Circuit 205, and a DSL Modem Digital Circuit 230. Except for those portions necessary for implementing the xDSL digital link of the present invention, the specifics of these two circuitry sections are well known in the art, and any suitable

5 hardware/logic/firmware combination could be used for effectuating the typical functions of an xDSL modem. For example, DSL Modem Analog Circuit 205 is typically a combination of a codec and various analog components necessary to support an xDSL link. It will be apparent to those skilled in the art that portions of DSL Modem Analog Circuit 205, as well portions (or even all) of DSL Modem Digital Circuit 230 may be

10 implemented in single chip (IC) form either alone or in combination with a larger functional device. With reference to FIG. 2A again, DSL Modem Digital Circuit 230 includes circuitry for performing some of the necessary signal processing associated with an xDSL link,, data buffering, and host interface functions. Additional control logic sets up and maintains the xDSL compatible data link by responding to appropriate commands

15 from the host. It also receives hardware status such as power loss detection from the DSL Analog Circuit 205 via the DSL link and passes this information forward to the host for necessary actions.

Various software drivers associated with the operating system can interact with DSL Modem Digital Circuit 230 through various available system busses such as a PCI

20 Bus to ensure proper data flow between such circuit and applications running on a host system. In a typical PC system, the functions performed by DSL Modem Digital Circuit 230 is embodied as part of a PCI Bus Controller chipset, such as those known in the art as either South Bridge or North Bridge. The purpose of this integration is to increase system integration flexibility and to reduce BOM costs. Thus, for purposes of the present

25 discussion, DSL Modem Digital Circuit 230 is also generally referred to herein as a DSL Digital IC, and this IC can be integrated alone as a standalone device, or, as noted immediately above, as part of a PCI North/South Bridge IC. In addition to DSL link, this overall chip may contain additional various interfaces such as a PCI bus 241, USB bus 242, and AC-Link 243. Furthermore, it may generate additional control signals such



Wake Up to the host for various modem operation needs. Other system controller functions (CPU, memory and PCI agent related) normally performed by such PCI Bus Controller chipset can be implemented in any conventional, well-known fashion.

In general, the hardware, firmware, software, and logic for performing the above  
5 functions in DSL Modem Digital Circuit 230 is dependent on the functions performed in  
DSL Modem Analog Circuit 205. For example, when oversampling is used in A/D and  
D/A, the digital filters for interpolation and decimation filters can be done on either side  
of the DSL link. Therefore, for purposes of the present invention, the actual  
implementation of DSL Modem Digital Circuit 230 and Digital Modem Analog Circuit  
10 205 can be accomplished through a number of variations that are compatible with the  
teachings herein. In many cases, as just described in connection with the filtering  
function, various signal processing or logic operations can be effectuated on either side of  
the link with no loss of performance or flexibility. The present invention, in fact,  
specifies a universal DSL link interface that allows a very flexible implementation for the  
15 two blocks and for future DSL technologies.

#### *DSL Analog Section Overview*

FIG. 2B provides a more detailed electrical schematic illustration of the  
components shown generally in FIG. 2A. As shown, a DSL Analog Modem Circuit 205  
20 is connected to a phone line through a hybrid circuit 207 and processes the received  
signal through a receive amplifier 209, filter 211, A/D 213, and, in embodiments where  
filtering is implemented on this side of the modem, a post digital filter 214. A ring detect  
circuit 212 is used to detect a remote wake up signal, which is some pre-designated xDSL  
signal. This wake up signal is passed on where it used, for example, to re-activate  
25 portions of the DSL modem and a host PC incorporating the same. A series of  
transmission counterpart stages are also shown in FIG. 2B, including a digital filter 214'  
(optional as noted above), D/A circuit 213', and a transmit amplifier and driver stage 211',  
for generating the xDSL analog transmit signal to the phone line through the hybrid. Also  
associated with DSL Analog Modem Circuit 205 is a DSL link interface block DSL-A

216, which transmits signals in the DSL link to DSL Digital Modem Circuit 230, and converts received signals in the DSL link to various data and control signals for the internal circuits within DSL Analog Modem Circuit 205, including control registers 215. Also inside DSL-A 218 is a clock circuit (not shown) which generates the necessary  
5 clocks for internal blocks and external DSL link based on an input from a System Master Clock as shown. Again, some or all of the functions of DSL Analog Modem Circuit 205 may be grouped and implemented in single chip form. For example, DSL-A codec 218, incorporating control registers 215, DSL-A Interface 216, digital filters 214, 214', and A/D 213 and D/A 213' is preferably embodied in a single integrated circuit (IC), and a  
10 separate IC is preferably used to embody analog front end sections (i.e. receive/transmit drivers 209, 209' and receive/transmit filters 211 and 211').

It should be emphasized that the above description is only a typical embodiment of DSL Analog Modem Circuit 205 suitable for use with the present invention, and that other variations of an analog codec circuit will be apparent to those skilled in the art.

15 Other voice modem related functions can also be incorporated in this stage, as noted in the aforementioned Intel specifications noted above.

To improve transmission performance against various noise sources from the PC motherboard and coupled to the components in the analog front end (AFE) section, DSL Modem Analog Circuit 205 can be physically placed in a separate printed circuit board  
20 (PCB) or riser card 211. This provides maximum noise isolation from DSL Modem Digital Circuit 230. This approach is similar to that done in the prior art for analog modems. Note that it is not necessary in all cases that DSL Modem Analog Circuit 205 be placed on a separate riser card 211, but it is important that such circuitry be isolated in some fashion so that it is substantially free from electronic noise that could impair its  
25 performance. Accordingly, DSL Modem Analog Circuit 205 could conceivably still be mounted on the same motherboard 231 as DSL Modem Digital Circuit 230, so long as the former is sufficiently isolated from other motherboard noise sources. As an example, a small isolating enclosure, shielding cage, or even insulative layer coatings might be used to protect and shield portions of DSL Modem Analog Circuit 205 from EMI and other

SUBA7

10054327-11301

noise, and this could result in smaller displacements between the analog and digital sections of an xDSL modem. Other appropriate manifestations will be apparent to those skilled in the art.

5 *DSL Digital Section Overview*

On the other side of DSL Link 220 is DSL Modem Digital Circuit 230, which includes a counterpart DSL-D Interface 233. As noted earlier, DSL Modem Digital Circuit 230 is preferably implemented as a single DSL Digital IC integrated within a South/North  
10 bridge controller within a PC system. The functions performed by this circuit include I/O transfers between a PC host and DSL Analog Circuit 205. Depending on the specific DSL implementation, part of the data pump functions can be done inside Receiver Buffer and Processing 234 and Transmitter Buffer and Processing 234'. For example, DSL functions such as IFFT and FFT can be performed by 234' and 234, respectively. DSL-D Interface  
15 233 interacts with and is responsible for coordinating data/control signals on the digital side of DSL Link 220. As with its counterpart on the analog side, DSL-A Interface 216, this circuit performs data conversion and control signaling via DSL Link 220. To interface with the PC host and various peripheral devices, DSL Digital IC 230 may also include various bus connections and interfaces. These include PCI Bus 241 and associated PCI Bus Interface 238 to the PC host, USB 242 and USB Interface 238' to  
20 external USB devices, and AC-Link 243 and DC97 Interface 238'' to external audio and analog modem codecs.

Again, it should be mentioned that the above description for the Digital IC 230 is but one typical embodiment for use with the present invention in a PC system, and that other variations of the same will be apparent to those skilled in the art. As noted earlier,  
25 some of the functions performed in DSL Digital IC 230 can instead be implemented on the analog side, and vice-versa.

As noted above, functions performed by Transmitter Buffer and Processing 234 and Receiver Buffer and Processing 234' depend on the specific xDSL implementation. In the case of host signal processing, where the present invention can be used for great

Sub 5

benefits, only minimal functions need be performed inside 234 and 234'. Instead, most xDSL functions are performed by the host CPU. The degree of integration of such functions by a CPU are, of course, a function of the available MIPs for performing the same. While it is not practical or economical at this time to implement a full rate ADSL data pump with contemporary CPU technologies, it is nevertheless quite possible to achieve reduced rate ADSL functionality (i.e., such as that specified by the proposed ITU-T G.992.2 standard) in a PC in most cases by utilizing the teachings of applicants' prior disclosures, including in serial nos. 08/884,895 and 08/884,957 which are hereby incorporated by reference. Thus, the hardware needed to implement DSL Digital IC 230 can be extremely inexpensive (simple interface circuitry) and cost-effective for a motherboard manufacturer.

#### *DSL Link Specification/Protocols*

A DSL link 220 couples DSL Modem Analog Circuit 205 to DSL Digital IC 230 through DSL-A Interface 216 and DSL-D Interface 233 respectively. This link includes a number of data and control signal lines. Specifically, there are four (4) receive data lines RX<sub>1</sub> - RX<sub>4</sub>; four (4) transmit data lines TX<sub>1</sub> - TX<sub>4</sub>; a variable rate bit clock signal (CLOCK); a word clock signal (WORD CLOCK) to show the word boundary for each sample; and a reset signal (RESET) from the DSL Digital IC 230 to reset the DSL Modem Analog Circuit 205. These signals are explained in detail below. As can be seen, the applicants have carefully evaluated and calculated an optimal set of data/control lines and signal formatting to minimize the total number of pin assignments and maximize the usability for various xDSL requirements.

Receive data lines RX<sub>1</sub> - RX<sub>4</sub> carry digital samples generated by A/D 213 and assembled and transmitted across the link by DSL-A Interface 216; DSL-D interface, conversely dis-assembles and passes these samples on for further signal processing. Unlike prior art audio modem codecs, which utilize a single receive data line, the present invention makes use of four parallel lines. This comes from a compromise between the single line prior art approach (which minimizes the number of pin assignments but

005432 444

Subm

requires a high clocking rate) and a fully parallel approach (which minimizes the clock rates but requires more driving power and a higher pin count). This compromise approach has the following advantages: (1) since xDSL signals are broadband signals, it minimizes clock frequencies and consequently device power consumption, (2) it reduces the total pin count to an acceptable level, (3) it provides an embedded channel for control signaling (explained shortly), and (4) enables various features such as using the same DSL link 220 as a logically equivalent Utopia interface (explained shortly).

For the same reasons, four (4) transmit data lines TX<sub>1</sub> - TX<sub>4</sub> carry digital samples from DSL Modem Digital Circuit 220 assembled by DSL-D Interface 233 into suitable form where they are then received and dis-assembled by DSL-A Interface 216 and processed by D/A converter 213' in DSL Modem Analog Circuit 205 to generate the analog transmit xDSL signal. Signal line RESET is activated when the PC host tries to reset DSL Modem Analog Circuit 205; this can occur, for example, when the xDSL modem must be initialized or re-initialized.

Signal line CLOCK carries a scalable rate clock signal,  $f_{\text{clock}}$  generated by the clock generator inside DSL-A 216, which can be any suitable and well-known conventional clocking circuit. For a given xDSL link of signal frequency bandwidth B, oversampling factor P, up to 15 bits per sample,  $f_{\text{clock}}$  is given by:

$$f_{\text{clock}} = 2 * B * P * 16/4$$

In a preferred embodiment, a sample word consists of 16 bits: 1 control bit and up to 15 sample bits. Therefore, the period of the signal line WORD CLOCK consists of four (4) serial clock periods. That is,

$$f_{\text{wc}} = f_{\text{clock}}/4$$

Unlike the prior art fixed clock rate signaling, the clock signal rates for CLOCK and WORD CLOCK will vary depending on the particular DSL link in place. The present DSL Digital Communication Link 220 does not impose any restriction on the clock rate, since it is expected that such should be scalable in a manner that supports a wide range of potential options for an xDSL modem in a personal computing system. In other words, this variability for the clock rate provides system motherboard manufacturers with the

ability to mix and match compatible combinations of digital and analog xDSL modem components without concern about the available clocking rate across the connecting interface. This optimizes options for both motherboard suppliers, and xDSL modem component vendors, since they only need to ensure that they are matching combinations of hardware that are otherwise compatible. For example, in an ADSL modem application, the T1.413 issue 2 standard calls for a full downstream (Nyquist) sampling rate of 2.2 MHz, where the signal bandwidth B is  $256 \text{ tones} * 4.3125 \text{ kHz/tone} = 1.1 \text{ MHz}$ . With P being 4X oversampling, CLOCK and WORD CLOCK are 35.328 and 8.832 MHz, respectively. The only important consideration, therefore, is to make certain that the particular DSL Digital IC 230 can support this clock rate in conjunction with the selected DSL Modem Analog Circuit 205. In this respect, therefore, DSL Digital Communications Link 220 supports a scalable clock rate that is based purely on the desired price and performance objectives of a system vendor. To flexibly adjust the clock rates, the external Master clock can be divided by a programmable value specified in a register inside DSL-A Interface 216, which can be set up by the host through the control channel embedded in the DSL Link 220 (explained shortly).

To reduce the total pin count in DSL Link 220, the same CLOCK and WORD CLOCK are used by the corresponding interfaces (DSL-A 216 and DSL-D 233) for both transmit and receive data.

The word clock rate,  $f_{wc}$ , provides timing for transmit and receive data samples. As illustrated generally in FIG. 3A, each pulse in the WORD CLOCK represents the beginning of a sample word. As shown, four sampling CLOCKS are used in a word period. This allows up to 16 bits ( $4 \text{ lines} * 4 \text{ cycles}$ ) per sample word. In a typical DSL application, a high speed codec will not require more than 15 bits per sample. Accordingly, the present scheme accommodates even the expected worst case for an xDSL modem by setting 16 bits per WORD CLOCK period, in which at least one of these bits can be designated for control signaling. Of course, while the preferred embodiment herein utilizes the specified clocking format discussed above, and an accompanying set of four data transmission lines, other combinations of these parameters

will be apparent to those skilled in the art from the present teachings. Accordingly, the present invention is not limited to any one particular combination of such parameters.

As mentioned above, the present invention also provides capability for communicating operational and/or control information easily and flexibly between the analog and digital sections of modem 200. This can be seen in FIG. 3B which illustrates how at least one operational control bit (D15) is reserved or allocated for an embedded operation channel (EOC). The EOC can be used, for example, for passing the following types of information across the link.

- (1) transmitter/receiver gains,;
- (2) interrupts to the Digital IC 230;
- (3) information to control VCXO in DSL Modem Analog Circuit 205 for timing recovery;
- (4) power management information, such as an ADSL wake-up signal, or a power loss signal received by DSL Digital IC 230 from the motherboard. The power loss signal from the motherboard, in the case of ADSL, is used by DSL Modem Digital Controller 230 for generating a dying gasp message to be transmitted to a remote transceiver through DSL Modem Analog Circuit 205. Other types of control information associated with a conventional xDSL link can also be accommodated.

It can be observed from FIG. 3B that EOC has an effective bit rate equal to the word clock. The present invention, therefore, provides a method for providing control signaling information that does not require a separate time division multiplexed control word sent over the link as is done in the aforementioned AC<sup>97</sup> prior art data link. This operational information is encoded by DSL-D Interface 233 into the data stream using any suitable logic, and is then decoded and acted upon by corresponding logic in DSL-A Interface 216 so that, for example, suitable adjustments are made to digital filters 214, 214', A/D 213, D/A 213', and amplifier and filter stages 209, 209' and 211, 211' respectively. This operational information can be passed in both directions across the link so that control registers 215 within DSL Analog Circuit 205 can be read or

configured in any desired manner by DSL Digital IC 230. Conversely, if desired, information concerning data and settings of control registers 235 within DSL Digital IC can be monitored and changed by control logic in DSL Analog Circuit 205.

Preferably, control information (i.e., control data or control data addressing) in the EOC is presented in asynchronous form in a manner analogous to that used in a conventional PC serial port or RS232 to simplify logic design. This means that a start bit is set to logical 0 when there is control data, and logical 1 otherwise. After the start bit, a fixed number ( $1+N_c$  or  $1+2 N_c$ ) of control bits fills out the remainder of the control word signal. To optimize the balance between short control words (to minimize delays) and long control words (improved addressing range), two different control word lengths are provided (i.e., the control word length is either  $N_c$  or  $2N_c$ ). To signal a short control word (say  $N_c=16$  bits), the bit immediately following the start bit is set to a logical 0; to signal a long control word (say 32 bits) the bit immediately following the start bit is set to a logical 1. Following the set of bits for the actual control word, the EOC is then stuffed with all logical 1 values, corresponding to idle bits. Because the above architecture is relatively flexible, it is of course possible (and may be desirable in some environments) to increase the number of embedded operation channels by using an additional bit (for example D 14) of the transmit/receive data words across the link.

## 20 *Additional Features in DSL Link*

### -- Variable Number of DSL Channels

Another useful aspect of the present invention is the provision in the present xDSL digital link for a variable number of channels. The aforementioned AC97 prior art can only handle a fixed number of channels (12) in the transmit/receive directions, and this is not practical for an xDSL link for a number of reasons. First, the receiving and transmitting data streams may not be operating at the same sampling clock. This will occur, for example, when there are different oversampling ratios, or where there are different signal bandwidths (e.g., ADSL) for upstream and downstream transmissions. Second, there may be multiple channels for transmission and receive directions. For



instance, an echo cancellation data path might be used in some environments for echo suppression. Finally, it may be useful to support additional DSL Modem Analog Circuits 205', 205'', (not shown) connected in parallel with DSL Modem Analog Circuit 205 using the same set of data signal, control and clock lines described above.

5 To achieve this variable number of channels capability, a frame structure for the word clock cycles is illustrated in FIG. 3C. As illustrated, a certain number M (programmable by software and set to a value of 2 as shown) of word clock cycles forms a frame clock to support M separate DSL channels (or separate analog circuits) in each direction. It is unnecessary, of course, for all M channels to be active at one time. To  
10 mark the beginning of a frame, the word clock is held high for a duration of two clock cycles. At startup, M is initially set to 1. To operate with multiple channels, DSL Digital IC 230 passes a control signal via the EOC noted earlier, to set M to some higher integer value in the DSL Modem Analog Circuit 205, such as  $M = 2$ . A multi-channel frame is then indicated by WORD CLOCK being set high for two clock cycles. As depicted in  
15 FIG. 3C, the data for channel 2 (or the second DSL Modem analog circuit) is presented at the beginning of the frame cycle (i.e., when WORD CLOCK is high for two cycles) and the data for channel 1 (or the first DSL Modem analog circuit) is presented during the second half of the frame cycle (during the time WORD CLOCK is high for a single cycle). Thus, in the multi-channel data frame of FIG. 3C, there are two data channels,  
20 and data is transferred through a first channel during a first time period of the multi-channel data frame, and through a second channel during a second time period of the multi-channel data frame.

In this manner, multiple codecs can be included in DSL Modem Analog Circuits 205. As is apparent, the value for M can be programmed as necessary by DSL Digital IC  
25 230 based on the particular DSL link requirements, the specific implementation of DSL Modem Analog Circuits 205, etc.

Furthermore, when the bit rates at the output of Digital Filters 214 and 214' have an integer relationship, the provision of multiple channels is a necessary feature. For example, in the case of ADSL where the sampling rates equal the Nyquist rates, the

upstream and downstream rates are 275 kHz and 2.2 MHz, respectively (a ratio of 1:8). Therefore, the present invention allows a DSL modem to be configured with a value of  $M=8$ , thus setting up only one active channel in the upstream direction and 8 active channels in the downstream direction.

5           The various clocks, buffers, latches, control logic, etc., for implementing this aspect of the present invention, as well as for performing the formatting, assembling, and dis-assembling operations on the Rx and Tx data samples by the various DSL-A and DSL-D interfaces are well-known in the art, and therefore any suitable combination of the same which effectuates the above functionality can be used for the present invention.

10

~~--Reuse of DSL Link for External Hardware DSL Implementation~~

~~As mentioned earlier, the use of DSL Link 200 is most attractive to a host based DSL modem implementation requiring minimal logic inside Digital IC 230. When the CPU in the motherboard is not fast enough, it is desirable to use the DSL Link to connect~~  
15 ~~Digital IC 230 to an external hardware DSL implementation. In this case, another useful aspect of the present invention is illustrated in FIG. 4. As shown, when an external hardware solution for a DSL modem implementation exists, a reasonable interface to use with such implementation is one based on the ATM Utopia I or Utopia II interface. This is because ADSL technology has already been defined to interface with ATM in both~~  
20 ~~T1.413 Issue 2 and ITU-T G.992 standards. In this configuration, DSL Digital IC 230 would be linked through DSL Digital Link 220 to a hardware based xDSL modem in FIG. 2A and 2B, instead of interfacing directly to DSL Analog Modem Circuit 205. In such instance, of course, since most of the signal processing and control functions would be located within the hardware xDSL modem, DSL Digital Controller 230 could be~~  
25 ~~simplified accordingly. The reason this is possible is because the same 10 signal lines described above (RX<sub>1</sub> - RX<sub>4</sub>, TX<sub>1</sub> - TX<sub>4</sub>, CLOCK and WORD CLOCK) can serve a dual purpose and act as an ATM interface as well. As above, for the same four sampling cycles per word clock, the following data can be transported over DSL digital link 220:~~

1.     First clock cycle period: RX<sub>1</sub> - RX<sub>4</sub> are used for Control, RxClav, TxClav;

~~TX<sub>1</sub> - TX<sub>4</sub> are used for Control, 0, RxEnb and TxEnb.~~

2. Second clock cycle period: ~~RX<sub>1</sub> - RX<sub>4</sub> are used for RxSoc, RxAddr [2:0], while TX<sub>1</sub> - TX<sub>4</sub> are used for TxSoc, TxAddr [2:0].~~
3. Third clock cycle period: ~~RX<sub>1</sub> - RX<sub>4</sub> are used for RxData [3:0], while TX<sub>1</sub> - TX<sub>4</sub> are used for TxData [3:0].~~
4. Fourth clock cycle period: ~~RX<sub>1</sub> - RX<sub>4</sub> are used for RxData [4:7], while TX<sub>1</sub> - TX<sub>4</sub> are used for TxData [4:7].~~

As defined above, the signals Control, RxClav, TxClav, RxEnb, TxEnb, RxSoc, TxSoc, RxAddr, and TxAddr are defined in the UTOPIA Specification, Level 1, Version 2.01, published March 21, 1994 by the ATM Forum, and incorporated by reference herein. It can be seen from the above that an ATM type interface can also be implemented by the DSL-A and DSL-D interfaces to exploit the embedded control channel characteristics of the present digital link with great advantage.

One significant advantage of the present invention, therefore, is the fact that the DSL Digital Link 220 can be incorporated within a motherboard of a personal computing system to enable great flexibility in configuring options for an xDSL communications capability. For example, a motherboard manufacturer (or ultimate system vendor) can configure any particular base level enabled system to include any desired level of xDSL modem performance and functionality, including either a host based soft modem solution, or a pure hardware type modem solution. This is accomplished by simply stuffing the board with various combinations; for example, a simplified version of DSL Digital Controller 230 can be combined with an ATM based hardware DSP xDSL modem, or, alternatively, a configuration such as shown in FIG. 2B can be implemented for a software modem implementation. The flexibility of the data lines of the communications link, and the use of an embedded control channel, permits easy adoption of optimized solutions for any particular application.

Thus, the configuration and selection of the data signal lines, the use of an embedded control channel, the data clocking mechanism, the ability to provide multiple data channels, and the format of control words used in the embedded control channel, all

contribute to making the present invention easily adaptable and usable with a number of different combinations of digital and analog circuits associated with xDSL modems.

Although the present invention has been described in terms of a preferred embodiment, it will be apparent to those skilled in the art that many alterations and  
5 modifications may be made to such embodiments without departing from the teachings of the present invention. Accordingly, it is intended that the all such alterations and modifications be included within the scope and spirit of the invention as defined by the following claims.

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214